Podešavanje automatskog dobijanja adrese na mrežnoj kartici:

U okviru **Start** menija koji se nalazi u donjem lijevom uglu radne površine



odaberite opciju Run...



Kada se otvori prozor ukucati: **control panel** i pritisnuti dugme **OK.** 





U prozoru koji se otvorio odabrati ikonicu Network connections.



U novom prozoru, čiji izgled može varirati od računara do računara, obilježiti opciju **Local area connection**\*, te kliknuti desnim tasterom miša da se dobije padajući meni.



Ovdje su bitne dvije opcije, opcija **Disable/Enable** (biće kasnije pojašnjena) i opcija **Properties** koja je bitna u ovom trenutku.

Disable <b>Status</b> Repair
Bridge Connections
Create Shortcut Delete Rename
Properties

Kada ste odabrali opciju Properties dobijate sledeci prozor:

onnect using:		
👜 SiS 900-Ba	sed PCI Fast Ethernet Ad	Configure
nis connection u	ses the following items:	
<ul> <li>Tom NWLink</li> <li>Tom NWLink</li> <li>Tom NWLink</li> <li>Tom NWLink</li> </ul>	NetBIUS IPX/SPX/NetBIOS Compati Protocol (TCP/IP)	ible Transport Prot
:)	III	
Install	Uninstall	Properties
Description		
	ontrol Protocol/Internet Prot ork protocol that provides co	ocol. The default ommunication
i ransmission Di wide area netw across diverse i	Interconnected networks.	

Selektujte opciju **Internet Protocol (TCP/IP)**, potom kliknite na dugme **Properties**.

U novom prozoru izaberite opciju **Obtain an IP address automatically** i gore i dolje (kao na slici).

Pritisnite dugme OK.

eneral Alternate Configuration	
You can get IP settings assigned a this capability. Otherwise, you nee the appropriate IP settings.	automatically if your network supports d to ask your network administrator for
Obtain an IP address automa	itically
-O Use the following IP address:	-
IP address:	1 - 24 - 25 - 14
Subnet mask:	20 20 12
Default gateway:	4-1 4-1 (+
Obtain DNS server address a	automatically
— Use the following DNS serve	r addresses:
Preferred DNS server:	80 EL 14
Alternate DNS server:	
	Advanced

Potom pritisnite dugme **Close** u prethodnom prozoru i sačekajte da se prozor uzgubi.

Ako računar nije dobio adresu ponekad je zgodno disable-ovati te potom opet enable-ovati karticu.

To se postiže odabirom opcije **Disable** iz gore pomenutog padajućeg menija:

Disable	N
Status	NG
Repair	
Bridge Co	nnections
Create Sh	ortcut
Delete	
Rename	
Propertie:	s.

Potom ponovo kliknite desnim tasterom da dobijete padajući meni i odaberite opciju **Enable**.

Fnable	
Create Sh	ortcut
Delete	oricat
Rename	
Properties	8

Sačekajte potrebno vrijeme i vaša kartica je spremna za rad.

\* Pošto može biti više Local Area Connection na vašem računaru postarajte se da ste odabrali pravu. Drugim riječima uvjerite se da nije Wireless ili Bluetooth ili 1394 (FireWire).