

PERIFERIJE I INTERFEJSI

O PREDMETU

Studijski programi za koje se organizuje :

- Osnovne studije, specijalističke studije Elektrotehnike - smjer Elektronika; Osnovne studije, studijski program D – PMF;

Uslovljenost drugim predmetima: Nema formalnih uslova. Podrazumijeva se poznavanje C/C++ jezika.

Ciljevi izučavanja predmeta: Interfejsi (međusklopovi) i periferije (spoljni uređaji) povezuju računare sa spoljašnjom sredinom. Cilj ovog predmeta je da studenti ovladaju znanjem i tehnikama, pomoću kojih će moći da, uz pomoć računara (automatski), prikupljaju informacije iz spoljašnjeg svijeta i da upravljaju procesima van računara. Osim teoretskog dijela, značajna pažnja se poklanja praktičnom radu.

Metod nastave i savladanja gradiva: Predavanja, računske vježbe i vježbe u računarskoj učionici/laboratoriji. Učenje i samostalna izrada praktičnih zadataka. Konsultacije.

O PREDMETU

Sadržaj predmeta:

Pripremna sedmica	Priprema i upis semestra
I sedmica	Uvod; Upoznavanje sa predmetom, ciljevima i načinom rada;
II sedmica	Mikrokontroleri; Razvojne ploče; Arduino Uno;
III sedmica	Izlazni portovi (Sedmosegmentni displeji, dot LED array, ...);
IV sedmica	Ulazni portovi;
V sedmica	Analogni ulazi i izlazi;
VI sedmica	Koračni motori;
VII sedmica	Optički interfejsi;
VIII sedmica	<i>Provjera znanja</i>
IX sedmica	Senzori i aktuatori (Servo motor, detektor pokreta, ...);
X sedmica	Senzori i aktuatori (Daljinski upravljači, ultrasonični senzori, ...);
XI sedmica	Komunikacioni interfejsi: -paralelni, -serijski; SPI, TWI (I ² C), UART, ZigBee ,...;
XII sedmica	WiFi funkcionalnost. Povezivanje mikrokon. uređaja na WiFi mrežu.
XIII sedmica	Primjene mikrokontrolerskog uređaja sa Wi-Fi funkcionalnošću;
XIV sedmica	Upravljanje mikrokontrolerskim uređajem pomoću mobilnog telefona;
XV sedmica	Modemi: AT komande, gsm, gprs, LoRa. Povez. mikrokon. uređ. sa modemom;
XVI sedmica	<i>Završni ispit</i>
Završna sedmica	Ovjera semestra i upis ocjena
XVIII-XXI sedmica	Dopunska nastava i popravni ispitni rok

O PREDMETU

Opterećenje studenata na predmetu

Sedmično

6 kredita x 40/30 = 8 časova

Struktura:

3 časa predavanja

1 čas računskih vježbi

4 časa samostalnog rada,
uključujući konsultacije

U toku semestra

Nastava i završni ispit: (8 časova) x 16 = 128 časova

Neophodne pripreme prije početka semestra
(administracija, upis, ovjera)

2 x (8 časova) = 16 časova

Ukupno opterećenje za predmet 6x30 = 180 časova

Dopunski rad za pripremu ispita u popravnom
ispitnom roku, uključujući i polaganje popravnog ispita
od 0 do 30 časova (preostalo vrijeme od prve dvije
stavke do ukupnog opterećenja za predmet 150
časova)

Struktura opterećenja:

128 časova (Nastava)+16 časova (Priprema)+36
časova (Dopunski rad)

Studenti su obavezni da pohađaju nastavu, rade i predaju sve domaće zadatke, odrade laboratorijske vježbe i obje provjere znanja.

O PREDMETU

Literatura:

Osnovna i pomoćna literatura u elektronskom obliku na www.ucg.ac.me/etf
Praktični zadaci za laboratorijske vježbe na www.ucg.ac.me/etf
Z.Mijanović i ostali, »Računarski interfejsi i periferije«, Univerzitet Crne Gore

Oblici provjere znanja i ocjenjivanje:

- Bodovi na vježbama 26 poena
- Provjera znanja 24 poena
- Završni ispit 50 poena.
- Prelazna ocjena se dobija ako se kumulativno sakupi najmanje 50 poena.


PERIFERIJE I INTERFEJSI

Interfejsi (međusklopovi) i periferije (spoljni uređaji) povezuju računare sa spoljašnjom sredinom.

Cilj ovog predmeta je da studenti ovladaju znanjem i tehnikama, pomoću kojih će moći:

- da uz pomoć računara (automatski) prikupljaju informacije iz spoljašnjeg svijeta,
- da upravljaju procesima van računara.



Računarski portovi




Senzori i attuatori




Kako povezati senzore i aktuatore sa računarom i korisnikom?




Mogu se povezati sa mikrokontrolerskom razvojnom pločom.





Povezivanje Arduino uređaja u sistem



Ne mora svaki Arduino uređaj direktno na internet.



Različite vrste senzorskih mreža



Senzorski uređaj




Senzorski uređaj sa funkcijom prenosa / ruter



Gateway


Povezivanje u oblak




IoT projekti




IoT oblasti primjene




Senzorske aplikacije za pamatniji svijet



IoT infrastruktura



Mikrokontrolerski uređaj (Senzorski čvor – Sensor node, Mote)



Što je mikrokontroler?






Fig. 0-1 Microcontroller versus Microprocessor

- Mali kompjuter u jednom čipu
Sadrži procesor, memoriju, i ulaze/izlaze
- Tipično je „**ugrađen**“ unutar nekih uređaja i kontroliše njihov rad
- Mikrokontroler je često mali i jeftin.

Što je mikrokontroler?




Što je razlika između ‘*Digital Input*’ i ‘*Analog Input*’?

Mikrokontroleri – definicija

- Programeri rade u virtuelnom svijetu.
- Uređaji rade u fizičkom svijetu.
- Kako povezati vituelni i fizički svijet?
- Uvedite mikrokontroler.
- Mikrokontroler je u osnovi mali računar koji posjeduje programabilne ulaze i izlaze opšte namjene.
- Ulazi mogu biti upravljani od strane fizičkog okruženja dok izlazi mogu upravljati fizičkim okruženjem.

Što je razvojna ploča?



- Štampana matična ploča dizajnirana da olakša rad sa mikrokontrolerom
- Razvojna ploča tipično uključuje:
 - napojno kolo;
 - programerski interfejs;
 - lako dostupne ulazno/izlazne pinove.

Arduino – Zvanična definicija

- Uzeto sa zvaničnog web sajta (arduino.cc):

Arduino je open-source elektronska prototipna platforma zasnovana na fleksibilnom, jednostavnom za upotrebu, hardveru i softveru.


Namijenjen je dizajnerima, hobistima, i svima drugima koji su zainteresovani za kreiranje interaktivnih objekata i okruženja.

Zašto Arduino?

- Bez obzira na razlog, Arduino platforma je postala defakto standard.
 - Postoji puno realizovanih, dostupnih, projekta koji koriste arduino platformu.
- Teži ravnoteži između jednostavnosti upotrebe i korisnosti.
 - Programski jezici se uglavnom vide kao glavna poteškoća.
 - Arduino C je značajno uproštena verzija C++.
- Nije skup.

Tipovi Arduino-a

- Više različitih verzija
 - Broj ulaznih/izlaznih kanala
 - Oblik (gabariti)
 - Procesorska snaga
- Leonardo
- Due
- Micro
- LilyPad
- Esplora
- Uno




Leonardo

- U poređenju sa Uno, malo unaprijedjen.
- Koristi ATmega32u4 mikrokontroler koji ima ugrađenu USB komunikaciju


■ Nema potrebe za dodatnim mikrokontrolerom

■ Može se prikazati PC-u kao miš ili tastatura



Due

- Mnogo brži procesor, mnogo više pinova
- Radi na 3.3 volta
- Izgledom sličan Mega



Micro

- Kad je veličina važna: Micro, Nano, Mini
- Uključuju sve funkcionalnosti Leonardo-a




LilyPad

- LilyPad je pogodan za primjenu na odjeći.



Esplora

- Game controller
- Sadrži džojstik, četiri tastera, linearni potencijometar (klizač), mikrofon, svjetlosni senzor, senzor temperature, tro-osni akceleromatar.
- Nema standardi set IO pinova.



Mega

- U poređenju sa Uno, Mega:
 - Mnogo više komunikacionih pinova
 - Više memorije




Arduino Uno


- Pinovi su grupisani u 3 grupe:
 - 14 digitalnih pinova
 - 6 analognih pinova
 - Napajanje
 - Pojavio se 2010



Arduino Uno razvojna ploča



ATmega328 unutrašnja architektura



(PCINT14/RESET) PC6	1	28	PC5 (ADC5/SCL/PCINT13)
(PCINT16/RXD) PD0	2	27	PC4 (ADC4/SDA/PCINT12)
(PCINT17/TXD) PD1	3	26	PC3 (ADC3/PCINT11)
(PCINT18/INT0) PD2	4	25	PC2 (ADC2/PCINT10)
(PCINT19/OC2B/INT1) PD3	5	24	PC1 (ADC1/PCINT9)
(PCINT20/XCK/T0) PD4	6	23	PC0 (ADC0/PCINT8)
VCC	7	22	GND
GND	8	21	AREF
(PCINT6/XTAL1/TOSC1) PB6	9	20	AVCC
(PCINT7/XTAL2/TOSC2) PB7	10	19	PB5 (SCK/PCINT5)
(PCINT21/OC0B/T1) PD5	11	18	PB4 (MISO/PCINT4)
(PCINT22/OC0A/AIN0) PD6	12	17	PB3 (MOSI/OC2A/PCINT3)
(PCINT23/AIN1) PD7	13	16	PB2 (SS/OC1B/PCINT2)
(PCINT0/CLKO/ICP1) PB0	14	15	PB1 (OC1A/PCINT1)

ATmega328 data sheet pp. 2, 5



ATmega328 karakteristike


Features

- High Performance, Low Power AVR® 8-Bit Microcontroller
- Advanced RISC Architecture
 - 131 Powerful Instructions – Most Single Clock Cycle Execution
 - 32 x 8 General Purpose Working Registers
 - Fully Static Operation
 - Up to 20 MIPS Throughput at 20 MHz
 - On-chip 2-cycle Multiplier
- High Endurance Non-volatile Memory Segments
 - 4/8/16/32K Bytes of In-System Self-Programmable Flash program memory
 - 256/512/512/1K Bytes EEPROM
 - 512/1K/1K/2K Bytes Internal SRAM
 - Write/Erase Cycles: 10,000 Flash/100,000 EEPROM
 - Data retention: 20 years at 85°C/100 years at 25°C⁽¹⁾
 - Optional Boot Code Section with Independent Lock Bits
 - In-System Programming by On-chip Boot Program
 - True Read-While-Write Operation
 - Programming Lock for Software Security
- Peripheral Features
 - Two 8-bit Timer/Counters with Separate Prescaler and Compare Mode
 - One 16-bit Timer/Counter with Separate Prescaler, Compare Mode, and Capture Mode
 - Real Time Counter with Separate Oscillator
 - Six PWM Channels
 - 8-channel 10-bit ADC in TQFP and QFN/MLF package
 - Temperature Measurement
 - 6-channel 10-bit ADC in PDIP Package
 - Temperature Measurement
 - Programmable Serial USART
 - Master/Slave SPI Serial Interface
 - Byte-oriented 2-wire Serial Interface (Philips I²C compatible)
 - Programmable Watchdog Timer with Separate On-chip Oscillator
 - On-chip Analog Comparator
 - Interrupt and Wake-up on Pin Change
- Special Microcontroller Features
 - Power-on Reset and Programmable Brown-out Detection
 - Internal Calibrated Oscillator
 - External and Internal Interrupt Sources
 - Six Sleep Modes: Idle, ADC Noise Reduction, Power-save, Power-down, Standby, and Extended Standby
- I/O and Packages
 - 23 Programmable I/O Lines
 - 28-pin PDIP, 32-lead TQFP, 28-pad QFN/MLF and 32-pad QFN/MLF
- Operating Voltage:
 - 1.8 - 5.5V
- Temperature Range:
 - -40°C to 85°C
- Speed Grade:
 - 0 - 4 MHz@1.8 - 5.5V, 0 - 10 MHz@2.7 - 5.5V, 0 - 20 MHz @ 4.5 - 5.5V
- Power Consumption at 1 MHz, 1.8V, 25°C
 - Active Mode: 0.2 mA
 - Power-down Mode: 0.1 µA
 - Power-save Mode: 0.75 µA (Including 32 kHz RTC)


ATmega328 data sheet p. 1

<http://ww1.microchip.com/downloads/en/devicedoc/doc2467.pdf>

Arduino Uno – električna šema



ATmega328 Microcontroller



Absolutni maximumi

28.1 Absolute Maximum Ratings*

*NOTICE:

Stresses beyond those listed under “Absolute Maximum Ratings” may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or other conditions beyond those indicated in the operational sections of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

Operating Temperature	-55°C to +125°C
Storage Temperature	-65°C to +150°C
Voltage on any Pin except $\overline{\text{RESET}}$ with respect to Ground	-0.5V to $V_{CC}+0.5V$
Voltage on $\overline{\text{RESET}}$ with respect to Ground.....	-0.5V to +13.0V
Maximum Operating Voltage	6.0V
DC Current per I/O Pin	40.0 mA
DC Current V_{CC} and GND Pins	200.0 mA


ATmega328 data sheet p. 316

Kako startovati?

Posjetite: <http://arduino.cc/en/Guide/HomePage>



1. Preuzmite & instalirajte Arduino environment (IDE)
2. Povežite ploču sa računarom pomoću USB kabla
3. Ako je potrebno, instalirajte dodatne drajvere
4. Pokrenite Arduino IDE
5. Selektujte razvojnu ploču
6. Selektujte serijski port
7. Otvorite blink primjer
8. Upišite program u razvojnu ploču
- ...
9. Pisanje vlastitog programa
10. Nerviranje/Debugiranje/Primoravanje da radi
11. Oduševljenje i neposredno započinjanje novog projekta
12. (spavanje samo kad se mora)

Arduino IDE



Pogledajte: <http://arduino.cc/en/Guide/Environment>
za više informacija

Odaberite serijski port i ploču



Razvoj Arduino programa

- Zasnovan na C++ bez 80% komandi.
- Pregršt novih komandi.
- Programi se nazivaju 'sketches' (skečevi, skice) .
- Skečevi obavezno sadrže dvije funkcije:
 - void setup()
 - void loop()
- setup() se pokreće prvi i samo jedanput.
- loop() se pokreće neprestano, dok se ne isključi napajanje ili se ne učitava novi skeč.

Arduino C


- Arduino skečevi uglavnom upravljaju pinovima na arduino ploči.
- Arduino skečevi su uvijek petlja.
 - void loop() {} je isto što i while(1) { }

Arduino tajming

- `delay(ms)`
Pauza nekoliko milisekundi
- `delayMicroseconds(us)`
Pauza nekoliko mikrosekundi
- Više komandi: arduino.cc/en/Reference/HomePage

Osobine kompajlera

- Brojni jednostavni skečevi su uključeni u kompajler
- Nalaze se pod opcijom File, Examples
- Kada je skeč napisan, može se upisati u programsku memoriju mikrokontrolera na Arduino štampanoj ploči kroz opcije File, Upload, ili pritiskom na <Ctrl> U



The screenshot shows the Arduino IDE interface with the 'Blink' sketch loaded. The code is as follows:

```
/*
  Blink
  Turns on an LED on for one second, then off for one second, repeatedly.

  This example code is in the public domain.
  */

// Pin 13 has an LED connected on most Arduino boards.
// give it a name:
int led = 13;

// the setup routine runs once when you press reset:
void setup() {
  // initialize the digital pin as an output.
  pinMode(led, OUTPUT);
}

// the loop routine runs over and over again forever:
void loop() {
  digitalWrite(led, HIGH); // turn the LED on (HIGH is the voltage level)
  delay(1000);             // wait for a second
  digitalWrite(led, LOW);  // turn the LED off by making the voltage LOW
  delay(1000);             // wait for a second
}
```

At the bottom of the window, a status bar indicates '3' and 'Arduino Uno on COM7'. A 'Save Canceled.' message is visible in the bottom left corner of the IDE window.

Arduino oprema

Keyes RFID Learning Module Set for Arduino



Konkurencija Arduinu



- Alternative Arduino platformi
 - Pinguino – PIC kontroler
 - MSP430 – Texas Instruments;
 - Drugi: korisnički, Teensy, itd.
- Netduino
- Računari
 - Raspberry Pi
 - BeagleBones – TI; ima računar i kontroler

Netduino

- Mikrokontroler i razvojno okruženje kreirano od strane Microsoft-a za rad sa .NET Micro Framework.
- DALEKO moćnije razvojno okruženje.
- Razlike
 - Pinovi na Netduino su 3.3V (ne 5V).
 - Netduino ima mnogo brži procesor
 - 60K RAM-a (naspram Uno-vih 2K).
- U velikoj mjeri kompatibilan sa Arduino-om, ali nije potpuno izmjenjiv.

Šildovi (Dodaci)

- Šildovi su ploče koje se dodaju na Arduino ploču.
- Oni proširuju mogućnosti Arduina.
- Primjeri:
 - Ethernet
 - GPS
 - Motor
 - Prototip
- shieldlist.org



Zaključak

- Arduino platforma predstavlja jeftin način da se uđe u svijet robotike.
- Arduino ima:
 - Brojne korisnike
 - Bogatu online biblioteku kodova i projekata

Kraj